

DCP-7055

TN2010/ DR2200



## **Compact Mono Laser All-in-One Printer**



With the DCP-7055 even small businesses can afford laser quality printing and copying plus colour scanning (including to PDF). It's quick, printing and copying 20 pages per minute (the first in less than 10 seconds) so you're not hanging around, while the 250-sheet paper capacity cuts down re-loading to save even more time. The separate drum and toner design means you only need replace whichever has run out to keep costs down. While Energy Star approval and a free 12-month warranty with lifetime technical support give you peace of mind.

## **Catalogue Spec**

- Low cost and compact makes this ideal for a small office
- Save time with fast 20ppm copy and print speed
- First page out time of less than 10 seconds
- High resolution colour scanning plus scan to PDF feature
- Separate drum and toner to help keep costs down only replace the one that's run out
- Less refilling with a 250 sheet paper capacity
- Hi-Speed USB 2.0 connection
- Added peace of mind with free 12-month warranty and lifetime technical support
- Green and clean technology that meets Energy Star environmental standard



## **Detailed Spec**

General

Engine Electrophotographic Laser
Processor ARM946E-S 200MHz
Local Interface Hi-Speed USB 2.0
LCD Display Size 2 lines x 16 characters
Memory Capacity 16MB (RAM)
On / Off Switch Yes

**Mono Printer** 

SpeedUp to 20ppm (pages per minute)ResolutionHQ1200 (2,400 x 600 dpi) quality

First Print Out Time [From Ready Mode] Less than 10 seconds
Warm Up Time [From Sleep Mode] Less than 7 seconds
Emulation GDI (host based)

**Mono Copier** 

Speed Up to 20cpm (copies per minute)

First Copy Out Time (From Ready Mode) Less than 12 seconds Resolution 600 x 600 dpi

Multi-Copying / Stack Makes up to 99 copies of each page

Enlargement / Reduction Ratio Easily copy documents to a required paper size (25% to 400% in 1% increments).

Save Paper Copy 2 or 4 pages to a single page (N-up copying)

Colour Scanner

Resolution (Optical) Up to  $600 \times 2,400 \text{ dpi}$  Resolution (Interpolated) Up to  $19,200 \times 19,200 \text{ dpi}$ 

Colour Depth 48bit internal / 24bit external colour scanner

Grey Scale 256 shades of grey are available for copying or scanning

TWAIN Scanner Compliance Windows® 7, Windows Vista®, Windows® XP, Windows® 2000 and OS X 10.3.9 or greater

WIA Scanner Compliance Windows® 7, Windows Vista®, Windows® XP

SANE Scanner Compliance Linux

Scan To E-mail, image, OCR, file (Requires the Brother Control Centre software)

Scan Key Enables user to scan a document to e-mail, image, OCR, file using the scan key (Requires the

Brother Control Centre software)

**Printer Driver** 

Windows 7 (32 & 64 bit editions), Windows Vista (32 & 64 bit editions), Windows XP Home

Edition, Windows XP Professional (32 & 64 bit editions), Windows \* 2000 Professional, Windows \* Terminal Services 2003 & 2008+++, Citrix Presentation Server+++ \*, Citrix

XenApp+++\*, Citrix Desktop+++
Apple Macintosh

Mac OS X 10.4.11 or greater

Linux\*\*\* CUPS printing system(x86, x64 environment), Linux printer driver for LPD/LPRng printing

system(x86, x64 environment)

**Printer Driver Installation Options** 

Installation Wizard An easy to use wizard that will guide you through whole installation process

Printer Driver Only Install only the printer driver using your own installation method

Driver Deployment Wizard [DDW]\*\*\* Guides you through the printer driver install and creates an executable file that can be used to

install the printer driver on other PC's (Windows® only).

Printer Driver Functions

N-up Printing (Windows<sup>®</sup> & Mac only)

Reduce up to 2, 4, 9, 16 or 25 A4 pages into just one A4 page

Potent Printing 4

Reduce up to 2, 4, 9, 16 or 25 A4 pages into a pactor wing 4, 0, 16 or 25 A4 pages

Poster Printing † Enlarge 1 A4 page into a poster using 4, 9, 16 or 25 A4 pages
Watermark Printing † Watermark your documents with predefined text or with your own user-defined messages

Manual Duplex † Manually print to both sides of a piece of paper, supported by instructions given by the printer

driver

Booklet Printing † Print documents in A5 Booklet format using manual duplex

**Remote Management Utilities** 

E-mail reports Reports containing basic usage data sent to a nominated e-mail address on a cyclical basis.

This feature requires the Brother BRPrint Auditor application\*\*\* to be installed onto the same

computer as the DCP-7055 / 7057.

E-mail notifications Alerts sent to a nominated e-mail address when anything which can disrupt printing activity

occurs. This feature requires the Brother BRPrint Auditor application\*\*\* to be installed onto

the same computer as the DCP-7055 / 7057.

Paper Handling
Paper Input\*\*

Standard Tray: 250 sheets Manual paper feed slot: 1 sheet

Paper Output\*\*

Face Down (standard output): 100 sheets
Face Up: 1 sheet (straight paper path) 1 sheet

Media Specifications

Media Types

Standard Tray Plain paper, thin paper, recycled paper

Manual paper feed slot: Plain paper, thick paper, recycled paper, bond paper, labels and envelopes



Media Weights

 Standard Tray:
 60 – 105g/m²

 Multi-Purpose Tray:
 60 – 163g/m²

Media Sizes

Standard Tray: A4, letter, B5(ISO/JIS), A5, A5 (long edge), B6(ISO), A6, executive

Multi-Purpose Tray: Width (76.2 – 220mm) x length (116.0 x 406.4)

List / Report

System Set-up List A printed report that shows the current setting of your machine.

Page Counters - Available to view in LCD & printed report

Total Print Pages Informs the user of the total number of all pages produced from this machine
Copy Pages Informs the user of the total number of copies made on this machine in pages
PC Print Pages Informs the user of the total number of PC prints from this machine
Report Pages Informs the user of the total number of reports printed on this machine in pages

Supplies

 Standard Toner (TN-2010)
 1,000 pages\*

 Drum (DR-2200)
 12,000 pages

The frequency of replacement of consumables will vary depending on the complexity of the prints, the percentage of coverage, paper size, page per job, and the type of media.

**Dimensions & Weights** 

 With carton & consumanbles
 527 (W) x 510 (D) x 440 (H) mm, 12.9Kg

 Without carton, with consumanbles
 405 (W) x 398.5 (D) x 268 (H) mm, 9.8Kg

**Power Consumption** 

Printing Average 445W at 25c Ready Average 55W at 25c Deep sleep Average 0.9w at 25c

Sound Pressure Level

Printing Less than 53 dB Ready Less than 30 dB

**Sound Power Level** 

Printing Less than 6.40B Ready Less than 4.22B

**Ecology** 

Typical Electrical Consumption (TEC) 0.968 kWh / week

Power Saving This enables the machine to consume less energy when not in use.

Toner Saving This reduces the toner usage and helps to reduce the total cost of printer ownership.

Energy Star Certified to the world-wide eco label for power consumption.

**Duty Cycles** 

Recommended 250-1,600 pages monthly print volume Maximum 8,000 pages monthly print volume

Contents

Toner cartridge: up to 700 pages\* (DCP-7055) Drum unit: up to 12,000 pages

Power supply cord

Driver software for Windows & Apple Macintosh

User Guide (CD-ROM) Quick Set-up Guide

PC interface cable **NOT** included

† For Windows only

†† Requires the Brother Control Centre Software

††† For USB printing only.

\*Approx. yield is declared in accordance with ISO/IEC 19752

\*\*Calculated with 80g/m² paper

\*\*\* Downloaded free of charge from Brother's Solutions Centre <a href="http://solutions.brother.com">http://solutions.brother.com</a>