HP LaserJet Pro 400 MFP M425



This networked MFP boosts productivity. Share resources with wireless networking, and print from virtually anywhere with HP ePrint. Improve workflow with access to business apps. Save time with automatic two-sided scanning and copying.



Increase productivity – even on the go.

- Scan documents directly to email or a network folder. Save time and get fast results: the dual head scanner means two-sided pages are only scanned once.
- Print at up to 33 ppm A4, and get a first page in as fast as eight seconds.
- Print from virtually anywhere with HP ePrint³. Send files from a smartphone directly to your printer using HP wireless direct printing^{1,2}.
- Set up and share anywhere in the office with wireless connectivity^{2,4}. Configure networking fast^{2,5}.

Produce high-quality documents time after time.

- Print professional-quality documents with bold text and sharp images, using Original HP LaserJet toner cartridges.
- Improve performance with trusted HP reliability. Do more with 800-sheets maximum paper input capacity (with optional 500-sheet tray).
- Save time with Original HP LaserJet toner cartridges that are reliable and feature an all-in-one design for easy
 installation.
- Print more affordably using an optional high-capacity Original HP LaserJet black toner cartridge⁶.

Easily manage print jobs and access business apps.

- Use business apps and an 8.89 cm (3.5-inch) colour touchscreen to access and print from the web or scan to online storage sites?.
- Manage workflow with intuitive features right on the printer: use the easy-access USB port to print from and save scans to – a flash drive.
- Easily control your print environment and save IT time and costs HP Web Jetadmin helps you monitor
 equipment and increase uptime.

Reduce your environmental impact.

- Reduce paper use by up to 50% with automatic two-sided printing.
- Save energy with HP Auto-On/Auto-Off Technology which turns your printer on when you need it and off when you don'te.
- Easily recycle Original HP LaserJet toner cartridges through HP Planet Partners¹⁰.
- This MFP's compact size is designed to use less space and create less packaging waste.

Highlights

- Print, copy, scan, digital sending and fax
- Print/copy up to 33 ppm
- 256 MB RAM, 800 MHz processor
- 1 Hi-Speed USB 2.0; 1 Host USB, I Walk-up USB
- Up to 1200 x 1200 dpi (with HP FastRes 1200)

HP LaserJet Pro 400 MFP M425

Technical specifications

Functions	Print, copy, scan, fax, walk-up USB
Print speed	Up to 33 ppm iSO black (AR): Up to 15 ipm duplex black (AA) Measured using ISO/IEC 24734, excludes first set of lest documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending or the system configuration, software application, driver, and document complexity. First page out 1.8 fast as 8 sec black (AB).
Print resolution	Up to 1200 x 1200 dpi black
Print technology	Laser
Print Area	Print margins: Top: 5 mm; Bottom: 5 mm; Left: 4 mm; Right: 4 mm; Maximum print area: 203 x 345 mm
Print languages	HP PCL 5e, HP PCL 6, HP Postscript Level 3 emulation, direct PDF (v 1.7) printing
Print cartridges number	1 (black)
Mobile printing capability	CF286A: HP ePrint, Apple AirPrint™, Mopria-certified, business applications; CF288A: H ePrint, Wireless direct printing, Apple AirPrint™, Mopria-certified, business applications
Monthly duty cycle	Up to 50,000 pages (A4); Recommended monthly page volume: 750 to 3000 pages
Automatic paper sensor	No
Processor speed	800 MHz
Display	8.89 cm touchscreen CGD (Colour Graphic Display)
Wireless	CF286A: No; CF288A: Yes, built-in WiFi 802.11 b/g/n, Wireless direct printing
Network ready	CF286A: Standard (built-in Gigabit Ethernet); CF288A: Standard (built-in Ethernet, Wireless 802.11 b/g/n)
Memory	Standard: 256 MB
Media types	Paper (plain, Green mode, light, heavy, bond, colour, letterhead, preprinted, prepunched recycled, rough); envelopes; labels; transparencies, cardstock
Media sizes	Supported A4; A5; A6; B5 (JIS); Custom: CF286R: Nultipurpose tray: 76 x 127 to 216 x 356 mm; tray 2 and optional 500-sheet tray: 105 x 148 to 216 x 356 mm; CF288A: Multipurpose tray: 76 x 127 to 216 x 356 mm; tray 2 and optional 500-sheet tray: 105 x 148 to 216 x 356 mm;
Media Handling	Input capacity: Up to 300 sheets Output capacity: Up to 150 sheets, Up to 10 envelopes Maximum: Up to 150 sheets Duplex printing: Automatic (standard)
Paper weight	Supported, by paper path: Tray 1: 60 to 163 g/m² (straight through paper path for special media); tray 2, optional 500-sheet tray 3: 60 to 120 g/m²; Automatic duplexer: 60 to 120 g/m²
Multitasking supported	Yes
Auto document feeder capacity	Standard, 50 sheets
Copier settings	Contrast (lighter/darker); resolution copy quality (text, mixed, picture, photograph, auto select); draft quality (on/off); multipage (on/off); reduce/enlarge 25 to 400%; copy collation; number of copies; one or 2-sided copying; tray select; paper size; paper type; restore default; Maximum number of copies: Up to 99 copies: Copy resolution: Up to 600 x 600 dp;; Copier resize: 25 to 4000;
Scanner specifications	Scanner type: Flatbed, 50-sheet ADF; Scan input modes: Front control panel Scan, Cop or Fax buttons, From PC: Solution Center Lite (Windows Vista) midnows VB10 Flow Stage (Windows* PX) To WAR-compliant or WHA-compliant or Software; Twain version: Version 1.9; Duplex ADF scanning: Ves, single pass duplex ADF; Scan size maximum (flatbed, ADF): 216 x 297 mm; Optical scan resolution: Up to 1200 dpi (colour and mono, flatbed): Up to 300 dpi (colour and mono, ADF)
Scan file format	PDF, searchable PDF, JPG, RTF, TXT, BMP, PNG, TIFF (scan to USB device and scan from the front panel to a network folder both only support JPG and PDF)
Scan speed	Up to 20 ppm (b&w), up to 9 ppm (colour)
Bit depth/ Greyscale levels	30-bit/ 256
Scannable area	Minimum media size: 48.8 x 48.8 mm; Maximum media size: 216 x 297 mm; Scannabla area (ADF): Minimum media size: 102 x 127 mm; Maximum media size: 216 x 381 mm ADF
Digital sending	Standard: Scan direct to email; scan to network folder; scan to Cloud
Fax	Yes, 33.6 kbps
Fax specifications	Fax memory: Up to 300 pages; Fax resolution: Standard: 203 x 98 dpj; Fine: 203 x 196 dpj; Superfine: 300 x 300 dpj (no halftone); Quick dialing: Up to 120 numbers (119 group dials); Broadcasting, maximum locations: 119

What's in the box	CF286A: HP LaserJet M425dn MFP; HP 80A Black LaserJet Toner Cartridge (~2700 pages); Getting Started Guide, Support flyer; CDs containing device software and electronic User's Guide; power cord(s); Phone cord(s); CF288A: HP LaserJet M4Z5dw MFP; power cord(s); HP 80A Black LaserJet Toner Cartridge (~2700 pages); Getting Started Guide, Support flyer; CDs containing device software and electronic User's Guide Phone cord(s); USE Called
Accessories	CF406A HP LaserJet 500-sheet Feeder/Tray
Supplies	CF280A IH B 0A Black Original Laser let Toner Cartridge 2,700 pages CF280X IH B 0X High Yield Black Original Laser let Toner Cartridge 6,900 pages Declared yield value in accordance with ISO/IEC 19752. Actual yields vary considerably based on images printed and other factors. For more information, visit http://www.hp.com/goleranboutsupple.
Software included	Windows®- HP Installer/Uninstaller, HP PCL 6 print driver, HP WIA Scan Driver, HP TWAIN Scan Driver, HP Scan, HP Fax Setup Wizard, HP Send Fax, HP Fax Print Driver; Mac: HP Installer/Uninstaller, HP Sed vier, HP Setup Assistant, HP Fax Print Driver, HP Ink Widget, HP Utility, Scan to email/folder setup
Printer management	Windows®: HP Device Toolbox (default install), SNP Alerts (minimum network install), HP Web Jetadmin (download); Mac: HP Utility
Compatible operating systems	Full software installs supported on: Windows 8, Windows 7 (32-bit and 64-bit), Windows Vista (32-bit and 64-bit), Windows Vista (32-bit d) (8P2 or higher); Driver only installs supported on: Windows Server 2008 (32-bit and 64-bit), Windows Server 2003 (32-bit) (SP3 or higher); Mac OS X v10.5, v10.6, v10.7; Lingus Linux: 9.4, 9.5, Red Hat Enterprise Linux: 5.0, 6.0, OpenSuSE: 11.3, 11.4, Fedora: 14, 15, Ubuntu: 10.04, 10.10, 11.04, Debian: 5.0, 6.0 and HPUX111
Minimum system requirements	Windows: Windows B, Windows 7 (32-bit/64-bit). Windows Vista (32-bit/64-bit). 1 GHz (32-bit) 686) or (64-bit) (640) processor. 1 GB RAM (32-bit) or 2 GB RAM (64-bit), 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows XP (32-bit) (52-2): Penitum* 233 MHz processor, 512 MB RAM, 400 MB free hard disk space, CD/DVD-ROM or Internet, USB or Network, port Mac. Mac. OS X v10.5, v10.5, v10.7; PowerP. C4, C5, or Intel® Core® Processor; 500 MB hard disk; CD-ROM/DVD-ROM or Internet; USB or Network
Printer dimensions (W x D x H)	CF286A: 439.9 x 382.7 x 423.5 mm; Maximum 439.9 x 633.4 x 660 mm (multipurpose tray and foldup cover extended; tray 2 extended to legal-size; ADF fully open) CF288A: 439.9 x 382.7 x 423.5 mm; Maximum 439.9 x 633.4 x 660 mm (multipurpose tray and foldup cover extended; tray 2 extended to legal-size; ADF fully open)
Package dimensions (W x D x H)	597 x 497 x 490 mm
Printer Weight	CF286A: 15.1 kg; CF288A: 15.1 kg
Package weight	19.6 kg
Operating environment	Temperature: 15 to 32.5°C, Humidity: 30 to 70% RH
Storage	Temperature: -20 to 40°C, Humidity: 10 to 90% RH
Acoustics	Acoustic power emissions: 6.4 B(A); Acoustic pressure emissions: 51 dB(A)
Power	Requirements: Input voltage: 220 to 240 VAC (*/- 10%), 50/60 Hz (*/- 2 Hz) Consumption: 600 watts (printing), 420 watts (copying), 10.5 watts (ready), 9.5 watts (sleep), 0.1 watts (fif). Typical Electricity Consumption (TEC): 2.67 kWh/Week Built-in power supply Power supply
Certifications	CISPR 22: 2005+A1/EN 55022: 2006+A1-Class B; EN 61000-3-2: 2006+A1+A2; EN 61000-3-3: 2006; EN 55024: 1998+A1+A2; FC Title 47 CFR, Part 15 Class B //CES-003, Issue 4; GB8254-2008, GB17625.1-2003 Energy Star Qualified: Yes
Country of origin	Product of China
Warranty	One-year warranty. Warranty and support options vary by product, country and local legal requirements. Please visit our website: http://www.bhp.com/uk/en/campaign/printer-repairs/printer-service.html
Service and support	USX82E HP 3 year Noxt Business Day Laser Jet M425 MFP Hardware Support USX88E HP 3 year Noxt Business Day Schrange Laser Jet M425 MFP Service USX04E HP 3 year Petturn Laser Jet M425 MFP Service USX49FE HP 1 year Post Warranty Next Business Day Laser Jet M425 MFP Hardware Support USX46FE HP 1 year Post Warranty Next Business Day Exchange Laser Jet M425 MFP Service USX47FE HP 1 year Post Warranty Return Laser Jet M425 MFP Service (USX83E/USZ46FE: Please check availability at Country level USX84E/USZ47PE: Central and Eastern Europe & Middle East, Mediterranean and Africa only)

Footnotes

Not available on all printers. Mobile device must be wireless-enabled. Printer must be HP ePrint-enabled. Feature may require driver or apps, available for download at www.hp.com/go/eprintcenter.; ² HP wireless direct printing, HP Auto Wireless Connect, and built-in wireless connectivity are only available on the HP Laser Jet Pro 400 MFP M425dw; ³ Requires an Internet connection to the printer. Feature works with any connected Internet- and email-capable device. Requires HP Web Services Account Registration. Print times may vary. For a list of supported documents, and image types, see www.hp.com/go/eprintcenter. And for additional solutions, see www.hp.com/go/mobile-printing-solutions., ⁴ Wireless performance is dependent upon physical environment and distance from access point, and may be limited during active VPN connections; ³ HP Auto Wireless Connect may not be available for all system configurations. Wireless performance is dependent upon physical environment and distance from access point. For information on compatibility, visit www.hp.com/go/autowirelessconnect.; ⁶ HP Auto Wireless performance is dependent upon physical environment and distance from access point. For information on compatibility, visit www.hp.com/go/autowirelessconnect.; ⁶ HP Box Laser-Jet Black Toner Cartridge not included; must be purchased separately.⁷ Requires a wireless access point and an Internet connection to the printer. Services may require registration. Availability varies by country, language, and agreements, and requires a firmware upgrade. For details, www.hp.com/go/eprintcenter.; ⁹ HP Auto-On/Auto-Off Technology capabilities subject to printer and settings; ¹⁰ Programme availability varies. HP cartridge return and recycling is currently available in more than 50 countries and territories around the world through the HP Planet Partners programme. For more information, or to request return envelopes and bulk collection boxes, visit www.hp.com/go/eprinter.





















The product could differ from the images shown. © Copyright 2015 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

